




Edge2 Station



Model	A1015																						
Overview	The Khadas Edge2 Station board expands the functions of Edge2 ARM PC by connecting to the Pogo Pads on the underside.																						
Highlights	Magnetic, adds ethernet, debug Uart and headphone support.																						
Tech Specs	<p>Functions</p> <table border="0"> <tr> <td>Ethernet</td> <td>10/100M, Registered Jack 45</td> </tr> <tr> <td>Debug Uart</td> <td>CP2104, USB-C Port</td> </tr> <tr> <td>DAC</td> <td>ALC4032-CG</td> </tr> <tr> <td>Headphone</td> <td>3.5mm Headphone Jack</td> </tr> </table> <p>LEDs</p> <table border="0"> <tr> <td>Power LEDs</td> <td>Green LED x1, Red LED x1</td> </tr> <tr> <td>Uart Data LEDs</td> <td>White LED x1, Blue LED x1</td> </tr> </table> <p>Power Support</p> <table border="0"> <tr> <td>Pogo Pins</td> <td>5V</td> </tr> <tr> <td>USB-C</td> <td>5V</td> </tr> </table> <p>PCB Board</p> <table border="0"> <tr> <td>Stackup</td> <td>4 Layers</td> </tr> </table> <p>Size</p> <table border="0"> <tr> <td>PCBA</td> <td>85.00mm (l) x 60.75mm (w) x 11.5mm (h)</td> </tr> <tr> <td>Acrylic Case</td> <td>86.00mm (l) x 60.75mm (w) x 15.0mm (h)</td> </tr> </table>	Ethernet	10/100M, Registered Jack 45	Debug Uart	CP2104, USB-C Port	DAC	ALC4032-CG	Headphone	3.5mm Headphone Jack	Power LEDs	Green LED x1, Red LED x1	Uart Data LEDs	White LED x1, Blue LED x1	Pogo Pins	5V	USB-C	5V	Stackup	4 Layers	PCBA	85.00mm (l) x 60.75mm (w) x 11.5mm (h)	Acrylic Case	86.00mm (l) x 60.75mm (w) x 15.0mm (h)
Ethernet	10/100M, Registered Jack 45																						
Debug Uart	CP2104, USB-C Port																						
DAC	ALC4032-CG																						
Headphone	3.5mm Headphone Jack																						
Power LEDs	Green LED x1, Red LED x1																						
Uart Data LEDs	White LED x1, Blue LED x1																						
Pogo Pins	5V																						
USB-C	5V																						
Stackup	4 Layers																						
PCBA	85.00mm (l) x 60.75mm (w) x 11.5mm (h)																						
Acrylic Case	86.00mm (l) x 60.75mm (w) x 15.0mm (h)																						
Documentation	<p>Schematic: http://dl.khadas.com/products/add-ons/edge2_station/schematic/edge2_station_sch_v12.pdf</p> <p>Silkscreen: http://dl.khadas.com/products/add-ons/edge2_station/schematic/edge2_station_silk_v2.pdf</p> <p>2D DXF Files: http://dl.khadas.com/products/add-ons/edge2_station/dxf</p> <p>3D CAD Files: http://dl.khadas.com/products/add-ons/edge2_station/cad</p> <p>Photos: http://dl.khadas.com/products/add-ons/edge2_station/photos</p>																						
Warranty [1]	1 Year Limited Hardware Warranty																						
Compatibility	Khadas Edge2																						
In the Box	Edge2 Station Board x1																						

[1] Khadas does not warrant against normal wear and tear, nor damage caused by accident or abuse.