Mind 2 AI Maker Kit BIOS Auto Power-On Configuration Guide

1. Restart the Mind 2 Al Maker Kit. When the screen goes dark, press and hold the **Delete** key to enter the BIOS menu.

2. Go to the **Advanced** menu, select **PCH-IO Configuration**, and press **Enter** to access the settings.

Main Advanced Security Boot	Aptio Setup – AMI Save & Exit	
 RC ACPI Settings CPU Configuration Power & Performance System Agent (SA) Configuration PCH-ID Configuration USB Configuration Network Stack Configuration NVMe Configuration VTIO 		<pre>PCH Parameters ++: Select Screen t1: Select Item Enter: Select +/-: Change Opt. F1: General Help F2: Previous Values F3: Optimized Defaults F4: Save & Exit ESC: Exit</pre>

3. Find **Auto Power On**, press **Enter**, set it to **Enable**, and press **Enter** again to confirm.

Advanced	Aptio Setup — AMI		
PCH-IO Configuration Wake on WLAN and BT Enable Auto Power On	[Enabled] [Enable]	Specify what state to go to when power is re-applied after a power failure (G3 state).	
· ·		<pre>++: Select Screen 14: Select Item Enter: Select +/-: Change Opt. F1: General Help F2: Previous Values F3: Optimized Defaults F4: Save & Exit ESC: Exit</pre>	
Version 2.22.1295 Copyright (C) 2024 AMI			
Advanced	Aptio Setup — AMI		
PCH-IO Configuration Wake on WLAN and BT Enable Auto Power On	[Enabled] [Disable]	Specify what state to go to when power is re–applied after a power failure (G3 state).	
	Auto Power On Enable Disable	★+: Select Screen 11: Select Item Enter: Select +/-: Change Opt. F1: General Help F2: Previous Values F3: Optimized Defaults F4: Save & Exit	



4. Press F4 to save changes and exit the BIOS setup.



5. Press **Enter** to confirm and finalize the settings.